

## Dante 8 in 8 Out Network Audio Processor



S-TRACK® is top 3 audio processor factory in China. The majority of our member has been focusing on the AV field for more than 20 years. Dante 8 In 8 Out Network Audio Processor (TIGER 88N) can also be called as DSP or audio matrix, which device does not need CD-ROM. It comes with its own installation software, one device for one software version, solving the troubles caused by the loss of installation CD and confusion of multiple software versions.

## S-TRACK® Dante 8 In 8 Out Network Audio Processor (TIGER D88N) Product Introduction:

This S-TRACK® Dante 8 In 8 Out Network Audio Processor (TIGER D88N) is one of the main export models. Dante 8 In 8 Out Network Audio Processor (TIGER D88N) can be extended with USB interface, which can realize device upgrade function, USB music playback and recording function, 8-channel programmable GPIO control interface (customizable input and output).

## S-TRACK® Dante 8 In 8 Out Network Audio Processor (TIGER D88N) Product Parameters

Number of Analog Channels	8-CH Balanced/Line Inputs + 8-CH Balanced/Line Outputs
Network Channels	8 Dante Input Channels + 8 Dante Output Channels

Sampling rate	48k@24bit
Preamplification	51dB (3dB per file, 17 files in total)
Phantom Power	48V
Frequency Response	20Hz ~ 20K Hz, $\pm 0.3$ dB
THD + N	$\leq 0.005\%$ @1k, 4dBu
Digital-Analog Dynamic Range(A-weighting)	114dB
Analog-Digital Dynamic Range(A-weighting)	120dB
Input Impedance(Balanced)	20k $\Omega$
Output Impedance ( Balanced )	100 $\Omega$
EIN(A-weighting)	$\leq -125$ dBu
Channel Isolation	100dB @1k Hz, 4dBu
Common Mode Rejection	70dB @80 Hz
Maximum Input Level	18dBu
Maximum Output Level	18dBu
Background Noise	-90dBu
System Delay	$\leq 9$ ms
Working Power	AC110V-220V, 50Hz/60Hz
Working Temperature	0-40 $^{\circ}$ C
Chassis Size (WxDxH)	482*258*45(mm)

## **S-TRACK® Dante 8 In 8 Out Network Audio Processor**

### **(TIGER D88N) Product Features:**

1. Comprehensive matrix mixing function, 24bit/48KHz sampling frequency, high-performance A/D D/A converter and 32-bit floating-point DSP processor.
- ★2. DSP audio processing, built-in automatic mixing console, including mixing and automatic mixing functions, with mixing component control functions, as well as feedback cancellation module, echo cancellation module, noise cancellation module.
3. Input Per Channel: preamplifier, signal generator, expander, compressor, 5-band parametric equalization.
4. Output Per Channel: 31-segment graphic equalization, delay, divider, limiter.
5. Chinese name can be set independently for each channel.
6. Test signal generator, sine wave, pink noise, white noise, frequency and level selectable.
7. Input phase switch, mute switch, phantom power switch.
8. Output mute switch, phase switch for each channel.
9. Flexible switching between Chinese, Chinese Traditional and English languages.
10. One key to display all functional modules.
11. Random storage of Chinese help files and software.
12. Random generation of the central control code; power failure automatic protection memory function; one key reset function.
- ★13. Channel copy, paste, joint control function.

14. The same host allows 10 users to manage, the user name can be set to Chinese.
15. Equipment name can be modified, allowing Chinese name.
16. Editable preset mode, new, delete, modify, one key initialization, preset mode can be stored to computer and one key recovery.
17. Input and output channels can be independently set color, one-key recovery switch.
18. with camera tracking function, a camera can be independently preset position adjustment.
- ★19. Convenient Web Control: built-in web controller, in Windows, Android, iOS and other platforms can be quickly operated.
- ★20. Ethernet multi-purpose data transmission and control port, can support real-time management of single and multiple devices.
21. Intuitive image, simple and easy to understand graphical software control interface, to bring customers a fast, real-time operating experience.
- ★22. Equipment without CD-ROM, comes with its own installation software, a device for a software version, to solve the trouble caused by the loss of the installation CD and multiple software versions confusion.
- ★23. Expandable USB interface, which can realize the device upgrade function, USB music playback and recording function;.
- ★24. Configuration of bidirectional RS232 interface, RS485 interface, standard Ethernet control interface, 8-channel programmable GPIO control interface (customizable input and output).
- ★25. Support 8~100 groups of scene preset function.

26. Intuitive, graphical software control interface, can work in XP/Windows7, 8, 10 and other system environments.

## **S-TRACK® Dante 8 In 8 Out Network Audio Processor (TIGER D88N) Application Scenarios:**

S-TRACK® Dante 8 In 8 Out Network Audio Processor (TIGER D88N) supports local long-distance transmission, with DBOX, DMIC, etc., to achieve long-distance transmission in buildings and communities, which is suitable for large-scale multi-system interconnection projects such as hotels, supermarkets, gymnasiums, transportation hubs, theme parks, corporate headquarters, administrative centers, learning, and so on.

